

Table with columns: Instruction, Opcodes, B/T, Flags, Instruction, Opcodes, B/T, Flags, Instruction, Opcodes, B/T, Flags, Instruction, Opcodes, B/T, Flags. Rows list various instructions like CALL, LD, LDH, etc., with their opcodes and flags.

BUG: INC rr / DEC rr when rr is between &FE00- &FEFF will cause spikes to flicker on the GB230. HALT will set CPU but will not stop the CPU, but will 'skip' one command, so put a NOP after HALT

Black: GB280 & Z80
Blue: Z80 only
Red: GB230 only
Purple: Cpc Timings